

Appln. No.: 10/604,025
Amendment Dated May 11, 2007
Reply to Office Action of March 20, 2007

RECEIVED
CENTRAL FAX CENTER

FIS920030111

MAY 11 2007

Amendments to the Claims: This listing of claims will replace all prior versions, and listings, of claims in the application

We Claim:

1. (Cancelled)
2. (Cancelled)
3. (Currently Amended) A data transceiver comprising:

input means for supplying a differential input data signal;

a transmitter;

a receiver;

a data link between said transmitter and said receiver; and

output means for receiving a differential output data signal;

 - said transmitter for:

(a) receiving the differential input data signal from said input means;

(b) receiving a feedback signal from said receiver, and

(c) equalizing, in response to the received feedback signal, a data eye of the differential input data signal;
 - said receiver for:

(a) receiving the differential input data signal from said transmitter;

Appln. No.: 10/604,025
Amendment Dated May 11, 2007
Reply to Office Action of March 20, 2007

FIS920030111

(b) determining an extent of the data eye of the differential input data signal,

(c) developing the feedback signal in response to the determination of the extent of the data eye of the differential input data signal; and

(d) supplying the differential output signal to said output means, and

• said data link for conducting:

(a) the differential input data signal from said transmitter to said receiver, and

(b) the feedback signal from said receiver to said transmitter, and

including:

(a) a first line for conducting the data positive signal of the differential input data signal, and

(b) a second line for conducting the data negative signal of the differential input data signal,

(a) said input means include a serializer for developing from an input in parallel format the differential input data signal and supplying the differential input data signal to said transmitter in serial format,

(b) said output means include a deserializer for receiving from said receiver the serialized differential input data signal and developing from the serialized differential input data signal an output in serial format, and

Appln. No.: 10/604,025
Amendment Dated May 11, 2007
Reply to Office Action of March 20, 2007

FIS920030111

(c) said data link conducts the serialized differential input data signal from said transmitter to said receiver.

(a) said receiver further includes means responsive to the serialized differential input data signal for:

- (1) measuring a Bit Error Rate of the serialized differential input data signal,
- (2) calculating, from the measurement of the Bit Error Rate, the degree of the equalization needed to produce a desired data eye for the serialized differential input data signal,
- (3) developing, from the calculation of the degree of the equalization needed to produce a desired data eye for the serialized differential input data signal, the feedback signal, and
- (4) conducting the feedback signal to said data link, and

(b) said transmitter further includes:

- (1) means for generating a reference signal related to the common mode of the serialized differential input data signal,
- (2) means for comparing the reference signal with the feedback signal to develop a difference signal representative of the difference between the reference signal and the feedback signal,

Appln. No.: 10/604,025
Amendment Dated May 11, 2007
Reply to Office Action of March 20, 2007

FIS920030111

- (3) a driver circuit having a variable, frequency-selective gain to which the serialized differential input data signal is conducted, and
- (4) means responsive to the difference signal for controlling the amplification of said driver circuit to alter the data eye of the serialized differential input data signal.

4. (Currently Amended) A data transceiver comprising:

input means for supplying a differential input data signal;

a transmitter;

a receiver;

a data link between said transmitter and said receiver; and

output means for receiving a differential output data signal;

• said transmitter for:

(a) receiving the differential input data signal from said input means,

(b) receiving a feedback signal from said receiver, and

(c) equalizing, in response to the received feedback signal, a data eye of the differential input data signal;

• said receiver for:

(a) receiving the differential input data signal from said transmitter,

Appln. No.: 10/604,025
Amendment Dated May 11, 2007
Reply to Office Action of March 20, 2007

FIS920030111

(b) determining an extent of the data eye of the differential input data signal,

(c) developing the feedback signal in response to the determination of the extent of the data eye of the differential input data signal; and

(d) supplying the differential output signal to said output means, and

• said data link for conducting:

(a) the differential input data signal from said transmitter to said receiver, and

(b) the feedback signal from said receiver to said transmitter, and
including:

(a) a first line for conducting the data positive signal of the differential input data signal, and

(b) a second line for conducting the data negative signal of the differential input data signal.

(a) said input means include a serializer for developing from an input in parallel format the differential input data signal and supplying the differential input data signal to said transmitter in serial format,

(b) said output means include a deserializer for receiving from said receiver the serialized differential input data signal and developing from the serialized differential input data signal an output in serial format, and

Appln. No.: 10/604,025
Amendment Dated May 11, 2007
Reply to Office Action of March 20, 2007

FIS920030111

(c) said data link conducts the serialized differential input data signal from said transmitter to said receiver.

(a) said receiver further includes means responsive to the serialized differential input data signal for:

- (1) measuring a Bit Error Rate of the serialized differential input data signal,
- (2) calculating the degree of the equalization needed to produce a desired data eye for the serialized differential input data signal,
- (3) developing, from the calculation of the degree of the equalization needed to produce a desired data eye for the serialized differential input data signal, the feedback signal, and
- (4) conducting the feedback signal to said data link, and

(b) said transmitter further includes:

- (1) means responsive to a common mode signal representative of the common mode of the serialized differential input data signal for generating:
 - (i) a first reference signal representative of the level of the average common mode of the serialized differential input data signal,
 - (ii) a second reference signal representative of a level a prescribed amount above the average common mode of the serialized differential input data signal, and

Appln. No.: 10/604,025
Amendment Dated May 11, 2007
Reply to Office Action of March 20, 2007

FIS920030111

- (iii) a third reference signal, equal and opposite to the second reference signal, representative of a level a prescribed amount below the average common mode of the serialized differential input data signal,
- (2) means for comparing the reference signals with the feedback signal to develop:
 - (i) a first difference signal representative of the difference between the first reference signal and the feedback signal,
 - (ii) a second difference signal representative of the difference between the second reference signal and the feedback signal, and
 - (iii) a third difference signal representative of the difference between the third reference signal and the feedback signal,
- (3) means for selectively coupling:
 - (i) the first reference signal to said comparing means, and
 - (ii) the second reference signal and the third reference signal alternately to said comparing means,
- (4) a driver circuit having a variable, frequency-selective gain to which the serialized differential input data signal is conducted, and

Appln. No.: 10/604,025
Amendment Dated May 11, 2007
Reply to Office Action of March 20, 2007

FIS920030111

- (5) means responsive to the difference signals for controlling the amplification of said driver circuit to alter the data eye of the serialized differential input data signal.

5. (Original) A data transceiver according to claim 4 wherein the Bit Error Rate of the serialized differential input data signal is measured at selected sampling points across the data eye of the serialized differential data signal in time.

6. (Original) A data transceiver according to claim 5 wherein the amplitude of the data eye of the serialized differential input data signal is measured with the Bit Error Rate of the serialized differential input data signal to calculate the degree of the equalization needed to produce a desired data eye for the serialized differential input data signal.

7. (Cancelled)

8. (Cancelled)

9. (Currently Amended) A method of equalizing a data eye of a differential input data signal conducted from a first location to a second location through a data link, said method comprising the steps of:

supplying a differential input data signal to a first location;

conducting the differential input data signal from the first location to a second location through a data link;

determining, at the second location, an extent of the data eye of the differential input data signal;

developing, at the second location and from the determination of the extent of the data eye of the differential input data signal, an indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal;

FIS920030111

Appln. No.: 10/604,025
Amendment Dated May 11, 2007
Reply to Office Action of March 20, 2007

conducting, from the second location to the first location, the developed indication of the degree of the equalization;

equalizing, at the first location and in response to the indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal, the data eye of the differential input data signal; and

supplying the differential input data signal from the second location,

serializing an input in parallel format to produce the differential input data signal supplied to the first location, and

deserializing the serialized differential input data signal supplied from the second location to produce an output in parallel format.

- (a) the step of determining the extent of the data eye of the differential input data signal includes measuring the Bit Error Rate of the serialized differential input data signal,
- (b) the step of developing an indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal includes calculating, from the measurement of the Bit Error Rate, the degree of the equalization needed to produce a desired data eye for the serialized differential input data signal, and
- (c) the step of equalizing the data eye of the differential input data signal includes:
 - (1) generating a reference related to the common mode of the serialized differential input data signal,

Appln. No.: 10/604,025
Amendment Dated May 11, 2007
Reply to Office Action of March 20, 2007

FIS920030111

- (2) comparing the reference with the indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal, and
- (3) altering the data eye of the serialized differential input data signal according to the difference between the reference and the indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal.

10. (Currently Amended) A method of equalizing a data eye of a differential input data signal conducted from a first location to a second location through a data link, said method comprising the steps of:

supplying a differential input data signal to a first location;

conducting the differential input data signal from the first location to a second location through a data link;

determining, at the second location, an extent of the data eye of the differential input data signal;

developing, at the second location and from the determination of the extent of the data eye of the differential input data signal, an indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal;

conducting, from the second location to the first location, the developed indication of the degree of the equalization;

equalizing, at the first location and in response to the indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal, the data eye of the differential input data signal; and

supplying the differential input data signal from the second location.

Appl. No.: 10/604,025

FIS920030111

Amendment Dated May 11, 2007

Reply to Office Action of March 20, 2007

- (a) serializing an input in parallel format to produce the differential input data signal supplied to the first location, and
- (b) deserializing the serialized differential input data signal supplied from the second location to produce an output in parallel format,
- (a) the step of determining the extent of the data eye of the differential input data signal includes measuring the Bit Error Rate of the serialized differential input data signal,
- (b) the step of developing an indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal includes calculating, from the measurement of the Bit Error Rate, the degree of the equalization needed to produce a desired data eye for the serialized differential input data signal,
- (c) the step of equalizing the data eye of the differential input data signal Includes:
 - (1) generating:
 - (i) a first reference representative of the level of the average common mode of the serialized differential input data signal,
 - (ii) a second reference representative of a level a prescribed amount above the average common mode of the serialized differential input data signal, and
 - (iii) a third reference, equal and opposite to the second reference, representative of a level a prescribed amount below the average common mode of the serialized differential input data signal,

Appln. No.: 10/604,025
Amendment Dated May 11, 2007
Reply to Office Action of March 20, 2007

FIS920030111

- (2) selectively comparing the references with the indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal, and
- (3) altering the data eye of the serialized differential input data signal according to:
 - (i) the difference between the first reference and the indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal,
 - (ii) the difference between the second reference and the indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal,
 - (iii) the difference between the third reference and the indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal.

11. (Currently Amended) A method of equalizing a data eye of a differential input data signal conducted from a first location to a second location through a data link, said method comprising the steps of:

supplying a differential input data signal to a first location;

conducting the differential input data signal from the first location to a second location through a data link;

determining, at the second location, an extent of the data eye of the differential input data signal;

Appln. No.: 10/604,025
Amendment Dated May 11, 2007
Reply to Office Action of March 20, 2007

FIS920030111

developing, at the second location and from the determination of the extent of the data eye of the differential input data signal, an indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal;

conducting, from the second location to the first location, the developed indication of the degree of the equalization;

equalizing, at the first location and in response to the indication of the degree of the equalization needed to produce a desired data eye for the differential input data signal, the data eye of the differential input data signal; and

supplying the differential input data signal from the second location,

serializing an input in parallel format to produce the differential input data signal supplied to the first location, and

deserializing the serialized differential input data signal supplied from the second location to produce an output in parallel format,

wherein the Bit Error Rate of the serialized differential input data signal is measured at selected sampling points across the data eye of the serialized differential data signal in time.

12. (Original) A method of equalizing the data eye of a differential input data signal according to claim 11 wherein the amplitude of the data eye of the serialized differential input data signal is measured with the Bit Error Rate of the serialized differential input data signal to calculate the degree of the equalization needed to produce a desired data eye for the serialized differential input data signal.